

CONNECTOR	SIDE A - PINS AND PIN OUTS		SIDE B - PINS AND PIN OUTS	
SL1 ISA Bus Slot	01	+12V	01	+12V
	02, 03	Ground	02	+5V
	04	IOCHCK#	03, 04	Ground
	05	SD7	05	RES DRV
	06	SD6	06	+5V
	07	SD5	07	IRQ9
	08	SD4	08	-5V
	09	SD3	09	DREQ2
	10	SD2	10	-12V
	11	SD1	11	OWS#
	12	SD0	12	+12V
	13	IOCHRDY	13	Ground
	14	AEN	14	SMEMW#
	15	LA19	15	SMEMR#
	16	LA18	16	IOW#
	17	LA17	17	IOR#
	18	LA16	18	DACK3#
	19	SA15	19	DREQ3
	20	SA14	20	DACK1#
	21	SA13	21	DREQ1
	22	SA12	22	REFRESH#
	23	SA11	23	SYS CLK
	24	SA10	24	IRQ7
	25	SA9	25	IRQ6
	26	SA8	26	IRQ5
	27	SA7	27	IRQ4
	28	SA6	28	IRQ3
	29	SA5	29	DACK2#
	30	SA4	30	TC
	31	SA3	31	BALE
	32	SA2	32	+5V
	33	SA1	33	OSC
	34	SA0	34, 35	Ground
	35, 36	Ground	36	- LDEV1
	37, 38	+5V	37	+5V
	39	SBHE#	38	+5V
	40	LA23	39	MEMCS16#
	41	LA22	40	IOCS16#
	42	LA21	41	IRQ10
	43	LA20	42	IRQ11
	44	LA19	43	IRQ12
	45	LA18	44	IRQ13
	48	LA17	45	IRQ14
	49	MEMR#	48	DACK0#
	50	MEMW#	49	DREQ0
	51	SD8	50	DACK5#
	52	SD9	51	DREQ5
	53	SD10	52	DACK6#
	54	SD11	53	DREQ6
	55	SD12	54	DACK7#
	56	SD13	55	DREQ7
	57	SD14	56	+5V
	58	SD15	57	MASTER#
			58	Ground